# PowerHouse 535

LiFePO4 Portable Power Station

512Wh | 500W




"Power Meets Portability"



## Highlights

### InfiniPower™ 10 Years of Everyday Use




# Proven Durability



Our drop-proof design and material selection meet the requirements of industry testing standards to withstand any impact during outdoor adventures.

USB-C PD Fast Recharge



## **Features**

9 Ports For A Wide Array of Devices

The power station has all the ports you need to charge your devices and appliances. It is equipped with 4 AC ports, 3 USB-A ports, a USB-C port, and a car outlet.

# USB-C For Adapter-Free

Time to get rid of bulky adapters because charging your laptop at fast speeds only requires a single cable. See the power station recharge itself and give a high-speed charge to a wide range of devices.

## Power Saving Mode

Switching on the energy-saving mode will automatically turn off the power station once all your devices are fully charged to prevent wasting power.

## Powerfully Quiet

The power station operates at whisperquiet levels at all times thanks to an internal chip and intelligent Al algorithm, so you barely know it's on.

#### **Product Model**

PN	A1751
Model Name	PowerHouse 535

## Battery Info

Type of Battery	LiFePO4
Capacity	512Wh
Capacity	160000mAh
Cycle Life	3000+ (to 80%)
Power left after 1-year without using (from 100%)	56%



## Power Outputs

Maximum Output	716W	USB-A Total Output	36W
# of Output Ports	US/JP:9; EU/UK/CN:7	# of USB-C Output	1
# of AC Socket	US/JP:4; EU/UK/CN:2		TV 04.0V 04.4TV 04.
AC Rated Power	500W	USB-C Rated Power (per port)	5V=3A; 9V=3A; 15V=3A; 20V=3A (60W Max)
AC Surge Power	750W	USB-C Total Output	60W
AC Total Output	500W		
AC Auto Shut-Off	Power Save Mode On (2hr)	USB auto shut-off	Yes
# of USB-A Output	3	# of Car Outlet	1
USB-A Rated Power (per port)	5V=2.4A (12W Max)	Car Outlet Rated Power (per port)	10.8~14V=10A (120W Max)

## Power Inputs

Input Votage	100-240V
Total Input Power	180W (1x 60PD + 120W Adapter)
EST Recharge Time with DC Adapter + PD	3.4hrs (1x 60PD + 120W Adapter)
Use Ports While Recharging	Yes
# of DC Input	1
DC Adapter	Yes
DC Adapter Input Power	11-28V 10A (120W Max)
Recharge to 80%	DC Only: 3.2H PD Only: 7.5H DC+PD: 2.4H
EST DC Adapter Recharge Time	4.5hrs

DC Input Size	7909
# of PD Input	1
PD Input Power	5V=3A; 9V=3A; 15V=3A; 20V=3A (60W Max)
EST PD Recharge Time	9.5 Hours (1x 60W PD)
Solar Input Power	11-28V 10A (120W Max)
EST Solar Recharge Time	4.5hrs (120W) 5.4hrs(100W)
Solar Panel Compatible	Yes
MPPT Support	Yes

#### Illumination Information

Ambient Light	Yes
Light Temperature	2700K
<u> </u>	
Lightness Level	1
SOS Mode	Yes

#### Safety Information

Operation Temperature (°C/°F)	Charging: -20 -40°C / -4 -104°F Recharging: 0-40°C / 32-104°F
Overload Protection (AC)	>550W
Over-current Protection (USB-A)	>2.4A
Over-current Protection (USB-C)	>3.6A
Over-current Protection (DC)	>10A

### Package Content

Product	Anker PowerHouse 535
AC Adapter	1x 120W AC Adapter
Cable	Car Charging Cable
User Manual	User Manual

#### Weight & Dimension

Product Dimension	292*251*188 mm ; 11.5*9.9*7.4 in
Packaging Size(L*W*H)	340*354*225 mm; 13.39*13.94*8.86 in
Product Weight	7.6 kg ; 16.8 lb
Product Weight with Package	8.87 kg ; 19.55 lbs

Certification: CE / UL / RCM / RoHS / UN38.3 / MSDS